



MODEL

CODE

**MIDLAND G7 PRO****C1090**

After many years of success the glorious MIDLAND G7 - the transceiver most appreciated by fans of outdoor activities and the perfect combination of simplicity and efficiency – renovates and arises in new version “**G7 PRO**”.

As the previous version, the G7 PRO is a robust and **extremely reliable** device that guarantees years of good performances and is an excellent technological solution to communicate in many situations: in professional activities or in leisure time.

The **new and modern design** is the novelty that most affects at a first sight, as well as the **wider LCD display**, where all the icons and the activated functions can be clearly seen.

Thanks to the new case, the radio can be powered in **4 different ways!** Besides the NiMH battery pack, the rechargeable or alkaline batteries, G7 PRO can also use the new (optional) **Li-Ion 1200 battery pack PB-PRO** (cod. C1148) that makes the radio 20% lighter!

Apart from the external design, also the technological core of the radio has been totally renewed so as to improve the functions, the versatility and the performances.

The **Dual PTT** allows to transmit in high or low power so as to prolong the battery life; besides the **Side Tone** function eliminates the annoying rustle at the end of transmissions (this is possible if you communicate with the other radios that are equipped with the same function).

The **audio quality** has been considerably improved to guarantee clearer conversations.

The new case is equipped with an easy access in the battery compartment to facilitate any technical check.

#### **COMPLYING TO CE/99/05**

**COLOR:** Black

### **Main functions**

- Dual Band PMR446/LPD transceiver (G7 PRO) or PMR446 only (G7E PRO)
- Channels: 8 PMR446 / 69 LPD
- Output power: 500mW PMR446 / 10mW LPD
- Dual PTT for high/low power selection, to extend the battery life
- Wide LCD display
- Improved audio level
- Possibility to power the radio with a Li-Ion battery pack (optional)
- Dual Watch to monitor 2 channels
- Vibracall function
- 38 CTCSS tones and 104 DCS codes in tx/rx
- Keypad lock to avoid accidental pressure of the controls
- Low battery indicator
- VOX for hands-free conversations with 6 levels selectable
- CALL function with 5 melodies at your choice
- Automatic squelch adjustment
- Buttons for the channel selections
- SCAN function
- 2 Pin jack for ext speaker/mike/battery recharge

Specifications are subject to change without notice.

## Codes and packing:

G7 PRO is available in the following versions

**G7 PRO - Dual Band PMR446/LPD – blister packing: cod.C1090**

- 2 radios with belt clip
- 2 NiMH 800mAh battery packs
- 1 double desktop charger
- 1 wall adaptor

**G7E PRO - PMR446 only – blister packing: cod.C1090.01**

- 2 radios with belt clip
- 2 NiMH 800mAh battery packs
- 1 double desktop charger
- 1 wall adaptor

**G7 PRO - Dual Band PMR446/LPD – single packing: cod.C1090.02**

- 1 radio with belt clip
- 4 x AA NiMH 1800mAh batteries
- 1 wall charger

**G7 PRO mimetic – Dual Band PMR446/LPD – single packing: cod.C1090.03**

- 1 mimetic radio with belt clip
- 4 x AA NiMH 1800mAh batteries
- 1 wall charger

**G7 PRO UK - Dual Band PMR446/LPD – blister packing: cod.C1090.04**

- 2 radios with belt clip
- 2 NiMH 800mAh battery packs
- 1 double desktop charger
- 1 wall adaptor with UK plug

